# WALL OR CELING MOUNT EDGE LIT SINGLE FACE EXIT SIGNS RXT 0913

Project:	
Туре:	
Date:	
Prepared By:	



#### **DESCRIPTION**

The **Wall or Ceiling Mount Edge Lit Exit Signs** connect to the internal battery of the LED lamps, when utility power fails. It lights a path for no less than 90 minutes. Battery recharges automatically when power is restored and is fully charged within 24 hours.

# **DESIGN FEATURES**

#### **Electrical Specs**

- 120/277V V Triac Dimming
- Nickel Cadmium rechargeable battery
- Dual color LED lamp indicator
- Fully automatic operation
- 90 minutes of illumination in case of power failure
- Self testing
- Operating Temperature 32°F to 122°F

### Construction

- Clear Acrylic Thermoplastic faceplate
- Die cast aluminum housing
- Low profile edge-lit design

# **ORDER INFORMATION**

#### **Dimensions**

- 12.25" L X 1.62" W X 8.5" H (Wall)
- 12.25" L X 1.62" W X 9.75" H (Ceiling)

#### Installation

- Wall or Ceiling installation
- Universal mounting canopy that pivots for slope ceiling use
- Removable directional indicators included

#### **Certifications**

- UL listed for Damp location
- 5 year limited warranty
- Damp location

Model No.	Finish	Self Diagnostic
RXT 0913	Red with white housing, White end caps - RWH Red with brushed aluminum housing, black end caps - RBR	SD
	Green with white housing, White end caps - GWH Green with brushed aluminum housing, black end caps - GBR	

Example: RXT -0913-RWH-SD

